

## NX-P1202AV/P1302AU

### 2W VHF/UHF ANALOG PORTABLE RADIOS

Kenwood's ProTalk NX-P1202AV and NX-P1302AU portable two-way business radios deliver professional performance at an economical price point. Offering the ideal solution for communications in construction, manufacturing and warehousing, retail, hospitality, facility management and rental fleet applications. Engineered to provide superb ease of use and audio clarity, even in noisy environments and boasts rugged performance for dependable communications in all weather conditions. It's business done right!



### Simple Yet Tough

#### TOUGH & WATER RESISTANT <sup>\*2</sup>

Built to take rough treatment in stride, the ProTalk has passed the demanding IP54/55 dust and water intrusion tests – both with and without the KMC-45 optional speaker microphone. It also meets or exceeds 11 stringent MIL-STD 8 10 C/D/E/F/G environmental standards, including "driven rain".

#### POWERFUL YET NATURAL SOUND OUTPUT

BTL audio amplifier for powerful 1-watt output.

### Customize and Deploy

#### SECOND PTT

Make use of the Second PTT for giving different instructions to different staff as the radio allows the use of main channel plus another channel<sup>\*1</sup>.

#### SELECTABLE 7-COLOR LED

A large 7-colour LED indicator on the top panel illuminates to notify multi-status functions. <sup>\*1</sup>

#### CLONING

Customize the radio programming one time and use the optional Cloning Cable to rapidly program groups of ProTalk radios with the same settings.

### Secure

Confidentiality in radio communications is a KENWOOD priority, and helping to maintain a high level of security in analog mode is a 16-code voice inversion scrambler.

### Upgrade to Digital

#### COMPATIBLE WITH DIGITAL AND ANALOG

This radio allows to upgrade to digital at a later time if you decide to go digital from analog (requires license key). It enables to have dual mode NXDN digital and analog combined operation.

#### ENHANCED AUDIO QUALITY

Based on decades of experience with professional and high quality audio products, the NX-P1000 can be customized to deliver the best digital audio to business radio users with various language backgrounds.

#### DIGITAL TECHNOLOGY PROVIDES SUPERIOR CLARITY IN EXTENDED COVERAGE

As RF signal strength weakens with distance, analog reception becomes increasingly noisy. NEXEDGE - NXDN digital modulation technology improves audio recovery in fringe areas, thereby "effectively" increasing the usable coverage compared to analog.

### Other Features

- Voice Announcement • SCAN • VOX / Semi-VOX (headset required) <sup>\*1</sup>
- Button Lock • Time-out Timer • Battery Saver<sup>\*1</sup> • Calling Alert • QT / DQT
- Compander • Adjustable Microphone Gain • Low Battery Warning

<sup>\*1</sup>: PC programming required.

<sup>\*2</sup>: All interfaces must be fully sealed with appropriate covers or by designated genuine accessories.

## Accessories

All accessories may not be available in all markets. Contact an authorized Kenwood dealer for details and complete list of all accessories.

**KNB-45L**  
2,000mAh/7.4V  
Li-Ion Battery Pack



**KSC-35SK**  
Fast Charger  
For the KNB-45L/69L  
82LCM (3-Hour)



**KRA-22/23**  
VHF/UHF Low Profile  
Helical Antenna



**KMC-45D**  
Speaker Microphone



**KHS-31C**  
C-Ring PTT Ear  
Hanger Headset



**KNB-69L**  
2,550mAh/7.4V  
Li-Ion Battery Pack



**KSC-43K**  
Dual Chemistry  
Fast Charger  
For the KNB 29N/45L/69L/82LCM



**KRA-26/ 27**  
VHF Helical Antenna  
UHF Whip Antenna



**KHS-26**  
Earbud In-line  
PTT Headset



**KBH-10**  
Belt Clip



**KNB-82LCM**  
2,000mAh/7.4V, Intrinsically  
Safe Li-Ion Battery Pack

**KVC-22**  
DC Vehicular  
Charger Adapter



**KRA-41/42**  
VHF/UHF  
Stubby Antenna



**KHS-27A**  
D-Ring In-line  
PTT Headset



## Specifications

General	NX-P1202AV	NX-P1302AU
Pre-set Frequencies	151-159 MHz	451-470 MHz
Max. Channels per Radio	64 channels	
Number of Zones	4 zones	
Max. Channels per Zone	16 channels	
Channel Spacing		
Analog	25" / 12.5 kHz	
Power Supply	7.5 VDC ±20 %	
Battery Life (5-5-90)		
KNB-45L (2000mAh)	Approx. 115 hours	
KNB-69L (2550mAh)	Approx. 145 hours	
Operating Temperature(Radio only) <sup>2</sup>	-22°F to +140°F (-30°C to +60°C)	
Frequency Stability (-30 to +60°C; +25°C Ref)	±0.5 ppm	
Antenna Impedance	50 Ω	
Dimensions	(W x H x D) Projections Not Included	
Radio with KNB-45L/82LCM	2.13 x 4.84 x 1.32 in (54 x 123 x 33.5 mm)	
Radio with KNB-69L	2.13 x 4.84 x 1.48 in (54 x 123 x 37.5 mm)	
Weight		
Radio Only	5.64 oz (160 g)	
Radio with KNB-45L/82LCM	9.88 oz (280 g)	
Radio with KNB-69L	10.41 oz (295 g)	
FCC ID	K44501000	K44501101

<sup>1</sup> 25 / 30 kHz in VHF/UHF Bands excluding T-Band are not included in the models sold in the USA or US territories.  
<sup>2</sup> Operating temperature specification for a Li-Ion battery is -10°C to +60°C [14°F to +140°F].

Specifications shown are typical and subject to change without notice, due to advancements in technology. Details and timing of firmware and software updates are subject to change without notice. Analog measurements made per TIA603. Specifications are measured according to applicable standards. All interfaces must be fully sealed with appropriate covers or by designated genuine accessories.

Receiver	NX-P1202AV	NX-P1302AU
Sensitivity		
Analog @ 12.5/25 kHz (12 dB SINAD)		0.20 μV / 0.24 μV
Selectivity		
Analog @ 12.5 / 25 kHz		68 dB / 74 dB
Intermodulation Distortion		70 dB
Spurious Rejection		70 dB
Audio Distortion		7%
Audio Output Power		1 W / 12 Ω (Internal Output) 500 mW / 8 Ω (External Output)
Transmitter	NX-P1202AV	NX-P1302AU
RF Power Output <sup>2</sup> (High / Low)		2 W / 1 W
Spurious Emission		-70 dB
FM Hum & Noise		
Analog @ 12.5 / 25 kHz		40 dB / 45 dB
Audio Distortion		2%
Emission Designator		16K0F3E, <sup>1</sup> 11K0F3E, 8K30F1E, 8K30F1D, 8K30F7W, 4K00F1E, 4K00F1D, 4K00F7W, 4K00F2D

FleetSync<sup>®</sup> is a registered trademark of JVCKENWOOD Corporation in the United States and/or other countries.  
NEXEDGE<sup>®</sup> is a registered trademark of JVCKENWOOD Corporation.  
ProTalk<sup>®</sup> is a registered trademark of JVCKENWOOD Corporation.  
AMBE+2<sup>™</sup> is a trademark of Digital Voice Systems Inc.  
All other trademarks are the property of their respective holders.

## MIL-STD & IP

MIL Standard	MIL 810C Methods/Procedures	MIL 810D Methods/Procedures	MIL 810E Methods/Procedures	MIL 810F Methods/Procedures	MIL 810G Methods/Procedures
Low Pressure	5001/Procedure I	5002/Procedure I, II	5003/Procedure I, II	5004/Procedure I, II	5005/Procedure I, II
High Temperature	5011/Procedure I, II	5012/Procedure I, II	5013/Procedure I, II	5014/Procedure I, II	5015/Procedure I, II
Low Temperature	5021/Procedure I	5022/Procedure I, II	5023/Procedure I, II	5024/Procedure I, II	5025/Procedure I, II
Temperature Shock	5031/Procedure I	5032/Procedure I	5033/Procedure I	5034/Procedure I, II	5035/Procedure I
Solar Radiation	5051/Procedure I	5052/Procedure I	5053/Procedure I	5054/Procedure I	5055/Procedure I
Rain*	5061/Procedure I, II	5062/Procedure I, II	5063/Procedure I, II	5064/Procedure I, III	5065/Procedure I, III
Humidity	5071/Procedure I, II	5072/Procedure II, III	5073/Procedure II, III	5074	5075/Procedure II
Salt Fog	5091/Procedure I	5092/Procedure I	5093/Procedure I	5094	5095
Dust	5101/Procedure I	5102/Procedure I	5103/Procedure I	5104/Procedure I, III	5105/Procedure I
Vibration	5142/Procedure VIII, X	5143/Procedure I	5144/Procedure I	5145/Procedure I	5146/Procedure I
Shock	5162/Procedure I, II, V	5163/Procedure I, IV	5164/Procedure I, IV	5165/Procedure I, IV	5166/Procedure I, IV

### International Protection Standard

Dust & Water Protection<sup>1</sup>

IP54/55\*

<sup>1</sup>To meet IP54/55, the 2-pin connector cover has to be connected on the radio or the locking bracket has to be attached to the external speaker microphone.

**JVCKENWOOD USA Corporation**  
Communications Sector Headquarters  
1440 Corporate Drive | Irving, TX 75038

Order Administration/Distribution  
P.O. BOX 22745, 2201 East Dominguez St., Long Beach, CA 90801-5745  
[www.kenwood.com/usa](http://www.kenwood.com/usa)

**JVCKENWOOD Canada Inc.**  
Sede central y distribución canadiense  
6070 Kestrel Road, Mississauga, Ontario, Canada L5T 1S8  
[www.kenwood.com/ca](http://www.kenwood.com/ca)

KENWOOD Communications  
Global Website



comms.kenwood.com



ISO9001 Registered  
Communications Systems Business Unit  
JVCKENWOOD Corporation  
ADS#03620 Print in U.S.A.